

ARCHITECT SWITCH SERIES



CRC3021



CRC3022



CRC3023



CRC3024



CRC3421

OVERVIEW

The Architect Series of wall switches provides user input to the 2-Wire System via simple push button interface for system control. There are one, two, three, and four button versions available as well as a dimmer style version. One, two, and three gang wall plates are available to create any button configuration required.

FEATURES

- Obtains power and communicates with other components using 2-Wire™ bus
- Multiple switches with same address can track and control same load
- ON/OFF status of the load is indicated via red (ON) or green (OFF)
- Switches and wall plates are plastic with brushed aluminum finish

SPECIFICATIONS

Input Signal:	±24VAC
Current Draw:	CRC3021 4.4 mA CRC3022 5.6 mA CRC3023 6.8 mA CRC3024 8.0 mA CRC3421 10 mA
Programming:	Via CRC6400
Temperature Rating:	0°-40°C (32°-104°F)

ORDERING INFORMATION

Part Number	Description
CRC3021	Architect Switch (1)
CRC3022	Architect Switch (2)
CRC3023	Architect Switch (3)
CRC3024	Architect Switch (4)
CRC3421	Architect Dimmer Switch
CRC9021	Architect 1 Gang Switch Plate
CRC9022	Architect 2 Gang Switch Plate
CRC9023	Architect 3 Gang Switch Plate